

MCXA153VLH_0P07H

Mask Set Errata



Mask Set Errata for Mask 0P07H

Revision History

This report applies to mask 0P07H for these products:

- MCXA152VFT
- MCXA153VLH
- MCXA152VFM
- MCXA143VLH
- MCXA143VFT
- MCXA143VFM
- MCXA142VLH
- MCXA142VFT
- MCXA142VFM
- MCXA153VFT
- MCXA153VFM
- MCXA152VLH

Table 1. Revision History

Revision	Date	Significant Changes
1.0	3/2024	Initial Revision

Errata and Information Summary

Table 2. Errata and Information Summary

Erratum ID	Erratum Title
ERR050501	Core: DFSR.EXTERNAL is not set correctly when waking up from sleep
ERR050502	Core: Execution priority might be wrong for one cycle after AIRCR is changed
ERR051588	LPSPi:Reset transmit FIFO after FIFO underrun by LPSPi Slave.
ERR051629	LPUART:Transmit Complete bit (STAT[TC]) is not set.
ERR051874	I2C clock stretching mode is not supported
ERR052138	Cannot connect to device with JTAG to enter debug if main flash and CMPA are empty (which is the status when device is out of manufacturing)

Known Errata

ERR050501: Core: DFSR.EXTERNAL is not set correctly when waking up from sleep

Description

Cortex-M33 1367266-C:

An external debug event which causes the processor to enter Debug state or the debug monitor should set DFSR.EXTERNAL. It has been found that this field is not set if the event occurs while the processor is asleep.

Workaround

There is no workaround.

ERR050502: Core: Execution priority might be wrong for one cycle after AIRCR is changed

Description

Cortex-M33 1435973-C:

AIRCR is used in the NVIC active tree to calculate the execution priority, which in turn is used to determine fault escalation, exception preemption, and other NVIC-related behaviors. When the active tree is pipelined and there are high latency IRQs active, there might be a glitch in the active tree output for one cycle after AIRCR is changed. The glitch results in NVIC producing wrong execution priority that is neither based on the old AIRCR value nor the new one.

Workaround

There is no workaround for this erratum.

ERR051588: LPSPi:Reset transmit FIFO after FIFO underrun by LPSPi Slave.

Description

Transmit FIFO pointers are corrupted when a transmit FIFO underrun occurs (SR[TEF]) in slave mode.

Workaround

When clearing the transmit error flag (SR[TEF] = 0b1) following a transmit FIFO underrun, reset the transmit FIFO (CR[RTEF] = 0b1) before writing any new data to the transmit FIFO.

ERR051629: LPUART:Transmit Complete bit (STAT[TC]) is not set.

Description

When the CTS pin is negated and the CTS feature is enabled (MODIR[TXCTSE] = 0b1) and the TX FIFO is flushed by software then, the Transmit Complete (STAT[TC]) flag is not set.

Workaround

Clear (MODIR[TXCTSE]) bit and reset the transmit FIFO (FIFO[TXFLUSH] = 0b1) when flushing the FIFO with CTS enabled (MODIR[TXCTSE] = 0b1).

ERR051874: I2C clock stretching mode is not supported

Description

I3C IP when working as I2C master mode it doesn't support Clock stretching feature.

Workaround

Application must not use I2C clock stretching feature. It will create clock contention on bus.

I2C Targets on the bus must keep Clock stretching feature disabled.

ERR052138: Cannot connect to device with JTAG to enter debug if main flash and CMPA are empty (which is the status when device is out of manufacturing)

Description

Cannot connect to device with JTAG to enter debug if main flash and CMPA are empty (which is the status when device is out of manufacturing).

Workaround

Use SWD to connect MCU first, after SWD connection establishing, use JTAG connection successfully.

Legal information

Definitions

Draft — A draft status on a document indicates that the content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included in a draft version of a document and shall have no liability for the consequences of use of such information.

Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <http://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

Suitability for use in automotive applications — This NXP product has been qualified for use in automotive applications. If this product is used by customer in the development of, or for incorporation into, products or services (a) used in safety critical applications or (b) in which failure could lead to death, personal injury, or severe physical or environmental damage (such products and services hereinafter referred to as "Critical Applications"), then customer makes the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, safety, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP. As such, customer assumes all risk related to use of any products in Critical Applications and NXP and its suppliers shall not be liable for any such use by customer. Accordingly, customer will indemnify and hold NXP harmless from any claims, liabilities, damages and associated costs and expenses (including attorneys' fees) that NXP may incur related to customer's incorporation of any product in a Critical Application.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Translations — A non-English (translated) version of a document, including the legal information in that document, is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Security — Customer understands that all NXP products may be subject to unidentified vulnerabilities or may support established security standards or specifications with known limitations. Customer is responsible for the design and operation of its applications and products throughout their lifecycles to reduce the effect of these vulnerabilities on customer's applications and products. Customer's responsibility also extends to other open and/or proprietary technologies supported by NXP products for use in customer's applications. NXP accepts no liability for any vulnerability. Customer should regularly check security updates from NXP and follow up appropriately.

Customer shall select products with security features that best meet rules, regulations, and standards of the intended application and make the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP.

NXP has a Product Security Incident Response Team (PSIRT) (reachable at PSIRT@nxp.com) that manages the investigation, reporting, and solution release to security vulnerabilities of NXP products.

NXP B.V. — NXP B.V. is not an operating company and it does not distribute or sell products.

Trademarks

Notice: All referenced brands, product names, service names, and trademarks are the property of their respective owners.

NXP — wordmark and logo are trademarks of NXP B.V.

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© NXP B.V. 2024.

All rights reserved.

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: salesaddresses@nxp.com

Date of release: 3/2024

Document identifier: MCXA153VLH_0P07H